

Figure 1
(PRIOR ART)



Before



After

Figure 1A

(PRIOR ART)



Figure 1B



Figure 2

Command	Transform Stall	Lighting Stall	Description
FE2XF_CMD_NOP			No operation. Can be used as a spacer between commands
FE2XF_CMD_VERTEX	read	read	Vertex data.
FE2XF_CMD_PASSTHR			Passthrough. Transform and lighting pass the data through.
FE2XF_CMD_RDVAB			Read the VAB contents when context switching.
FE2XF_CMD_LDMODE			Load new mode bits.
FE2XF_CMD_LDXFCTX	write		Load transform context memory data
FE2XF_CMD_RDXFCTX	read		Read transform context memory data.
FE2XF_CMD_LDLTCTX		write	Load lighting context memory data.
FE2XF_CMD_RDLTCTX		read	Read lighting context memory data.
FE2XF_CMD_LDLTC0		write	Load lighting context0 memory data.
FE2XF_CMD_RDLTC0		read	Read lighting context0 memory data.
FE2XF_CMD_LDLTC1		write	Load lighting context1 memory data.
FE2XF_CMD_RDLTC1		read	Read lighting context1 memory data.
FE2XF_CMD_LDLTC2		write	Load lighting context2 memory data.
FE2XF_CMD_RDLTC2		read	Read lighting context2 memory data.
FE2XF_CMD_LTLTC3		write	Load lighting context3 memory data.
FE2XF_CMD_RDLTC3		read	Read lighting context3 memory data.
FE2XF_CMD_SYNC	read+write	read+write	Similar to NOP, but is not allowed to be processed in parallel

Figure 2A



Figure 2B


50
230
ADDRESS
DATA
WA
WD VAB RD
RA
OUT
236
234
CLK
0
1
5
CLK
232
LOGIC
238

Figure 2C

Mode Bit	Bits	Description
T0	1	Texture 0 enable
TXF0	1	Texture 0 matrix transform enable
TDV0	1	Texture 0 w divide enable
T0S	3	Texture 0 texgen s control
T0T	3	Texture 0 texgen t control
T0U	3	Texture 0 texgen r control
T0Q	2	Texture 0 texgen q control
T1	1	Texture 1 enable
TXF1	1	Texture 1 matrix transform enable
TDV1	1	Texture 1 w divide enable
T1S	3	Texture 1 texgen s control
T1T	3	Texture 1 texgen t control
T1U	3	Texture 1 texgen r control
T1Q	2	Texture 1 texgen q control
ETY	1	Eye type infinite(0) or local(1)
LIT	1	Lighting enable
NRM	1	Normal normalize enable
FOG	1	Fog enable
LIS	16	Light status (8 lights by 2 bits each, 0:off,1:infinite,2:local, 3: spotlight)
FG	2	Foggen control (0: off, 1. radial, 2: plane)
LAT	1	Light attenuation control (0: invert, 1: no invert)
C1I	1	Specular color input enable
C1O	1	Specular color output enable
CM	4	Color material control (1: emissive, 2:ambient, 4: diffuse, 8: specular)
PP	1	Point parameter enable
SKIN	1	Skinning enable
VPAS	1	Vertex pass enable

Figure 3


VAB
50
IBuffer
400
412
410
52
micro-code
Transform
Context
Memory
VBuffer
WBuffer
TBuffer
402
404
406
408

Figure 4


START
420
DETERMINE CURRENT THREAD(T)
422
GET NEXT INSTRUCTION FOR T# USING CORRESPONDING PROGRAM COUNTER (PC#)
NEXT CYCLE
424
INJECT INSTRUCTIONS INTO PROCESSING MODULE(S)

Figure 4A


450
PC0
PC1
PC2
THREAD #
NEXT PC
CURRENT PC#
INSTRUCTION MEMORY
452
458
454
MLU
457
INSTRUCTION DELAY
456
ALU
457
INSTRUCTION DELAY
459
RLU/ILU

Figure 4B


52
400
IBuffer
514
smear
502
a
b
M
500
o
410
Context Memory
506
508
delay
a
b
A
504
o
[0]
32
a
I
o
512
a
R
o
ireg
Converter
510
516
518

Figure 5



Figure 6



Figure 7



Figure 8



Figure 9

Address	Target	Action	Description
TPOS	TBUFFER	T[0] = ALU	Position
TT0	TBUFFER	T[3] = ALU	Texture0
TT1	TBUFFER	T[4] = ALU	Texture1
WEV	WBUFFER,VBUFFER	W[0] = ALU, V[0].y = ALU.w	Eye vector
WLV0	WBUFFER,VBUFFER	W[1] = ALU, V[1].y = ALU.w	Light0 direction vector
WLV1	WBUFFER,VBUFFER	W[2] = ALU, V[2].y = ALU.w	Light1 direction vector
WLV2	WBUFFER,VBUFFER	W[3] = ALU, V[3].y = ALU.w	Light2 direction vector
WLV3	WBUFFER,VBUFFER	W[4] = ALU, V[4].y = ALU.w	Light3 direction vector
WLV4	WBUFFER,VBUFFER	W[5] = ALU, V[5].y = ALU w	Light4 direction vector
WLV5	WBUFFER,VBUFFER	W[6] = ALU, V[6].y = ALU.w	Light5 direction vector
WLV6	WBUFFER,VBUFFER	W[7] = ALU, V[7].y = ALU.w	Light6 direction vector
WLV7	WBUFFER,VBUFFER	W[8] = ALU, V[8].y = ALU.w	Light7 dirction vector
WSL0	WBUFFER	W[9] = ALU	Spotlight0 cos
WSL1	WBUFFER	W[10] = ALU	Spotlight1 cos
WSL2	WBUFFER	W[11] = ALU	Spotlight2 cos
WSL3	WBUFFER	W[12] = ALU	Spotlight3 cos
WSL4	WBUFFER	W[13] = ALU	Spotlight4 cos
WSL5	WBUFFER	W[14] = ALU	Spotlight5 cos
WSL6	WBUFFER	W[15] = ALU	Spotlight6 cos
WSL7	WBUFFER	W[16] = ALU	Spotlight7 cos
VED	VBUFFER	V[0].x = 1.0, V[0].z = ALU.w	Eye radial distance vector
VLD0	VBUFFER	V[1].x = 1.0, V[1].z = ALU.w	Light0 distance vector
VLD1	VBUFFER	V[2].x = 1.0, V[2].z = ALU.w	Light1 distance vector
VLD2	VBUFFER	V[3].x = 1.0, V[3].z = ALU.w	Light2 distance vector
VLD3	VBUFFER	V[4].x = 1.0, V[4].z = ALU.w	Light3 distance vector
VLD4	VBUFFER	V[5].x = 1.0, V[5].z = ALU.w	Light4 distance vector
VLD5	VBUFFER	V[6].x = 1.0, V[6].z = ALU.w	Light5 distance vector
VLD6	VBUFFER	V[7].x = 1.0, V[7].z = ALU.w	Light6 distance vector
VLD7	VBUFFER	V[8].x = 1.0, V[8].z = ALU.w	Light7 distance vector
VC0	VBUFFER,TBUFFER	V[9] = ALU, T[1] = ALU	Diffuse color
VC1	VBUFFER,TBUFFER	V[10] = ALU, T[2] = ALU	Specular color
VNRM	VBUFFER	V[11] = ALU	Normal vector
VED2	VBUFFER	V[12] = ALU	Eye planar distance vector
TVW_NOP			No valid output.

Figure 10

Microcode Field	Bits	Location	Delay	Description
oa	6	0: 5	2	Output buffer write address
rra	3	6: 8	0	RLU read address
rwm	4	9:12	2	RLU write mask
rwa	3	13.15	2	RLU write address
ilu	2	16:17	2	ILU operation
alu	4	18.21	1	ALU operation
ais	2	22·23	1	ALU sign control
aia	1	24	1	ALU input A mux
mlu	3	25·27	0	MLU operation
mib	2	28:29	0	MLU input B mux
mia	2	30:31	0	MLU input A mux
va	3	32:34	0	Input buffer read address
ce	1	35	0,2	Context memory read/write
ca	6	36.41	0,2	Context memory address
mr	2	42:43	0	MLU input vector rotate

Figure 11



Figure 12


RECEIVING A PLURALITY OF MODE BITS INDICATIVE OF THE STATUS OF A PLURALITY OF MODES OF PROCESS OPERATIONS
1320
IDENTIFYING A PLURALITY OF ADDRESSES IN MEMORY BASED ON THE MODE BITS
1322
ACCESSING THE ADDRESSES IN THE MEMORY FOR RETRIEVING CODE SEGMENTS WHICH EACH ARE ADAPTED TO CARRY OUT THE PROCESS OPERATIONS IN ACCORDANCE WITH THE STATUS OF THE MODES
1324
EXECUTING THE CODE SEGMENTS WITHIN A TRANSFORM OR LIGHTING MODULE FOR PROCESSING VERTEX DATA
1326

Figure 13


1430
MODE REG
MODE REG
MODE REG
CURRENT THREAD
1432
DECODE MODE BITS
CONTROL VECTOR
MASK
1434
NEXT POINTER
1436
1438
PRIORITY ENCODE
1404
ROM

Figure 14


1440
V
VECTOR OPERATIONS
V
V
1442
VECTOR OPERATIONS
S
SMEAR
V
V
x y z w
RLU
V
1444
1446
V
EXTRACT
S
ILU
S
SMEAR
V

Figure 14A


1442
V
V
1451
a b
VECTOR
OPERATIONS
V
S
SMEAR
V
V
EXTRACT
1446
S
SCALAR
OPERATIONS
S
SMEAR
V
V
x y z w
RLU
1444
V

Figure 14B


1453
VECTOR SOURCE
V
EXTRACT
1446
1442
V
S
SCALAR OPERATIONS
VECTOR OPERATIONS
S
V
S
SMEAR
SMEAR
V
V
V
x
y
z
w
RLU
1444
V
VECTOR DESTINATION

Figure 14C


RECEIVING A PLURALITY OF MATRICES, A PLURALITY OF WEIGHT VALUES EACH CORRESPONDING WITH ONE OF THE MATRICES, AND VERTEX DATA
1470
CALCULATING A SUM OF A PLURALITY OF PRODUCTS WITH EACH PRODUCT CALCULATED BY THE MULTIPLICATION OF THE VERTEX DATA, ONE OF THE MATRICES, AND THE WEIGHT CORRESPONDING TO THE MATRIX
1472
OUTPUTTING THE SUM OF PRODUCTS FOR ADDITIONAL PROCESSING
1474

Figure 14D



Figure 15



Figure 16



Figure 17



Figure 18



Figure 19



Figure 20

Name	Register	Description
Z	IFLAG	Clear flag. Sets IFLAG and MFLAG to 0.
C	IFLAG	Spotlight cone flag. Set if vertex is outside spotlight cone.
S	IFLAG	Specular2 flag. Set if specular contribution is negative.
D	IFLAG	Diffuse flag. Set if diffuse term is negative
	MFLAG	
U	MFLAG	Spotlight cone attenuation flag. Set if spotlight cone attenuation contribution is negative.
T	MFLAG	Specular flag. Set if specular contribution is negative
R	MFLAG	Range flag. Set if vertex is too far away from the light

Figure 21

Microcode Field	Bits	Location	Delay	Description
oa	3	0..2	2	Output address
rwe	1	3	2	RLU write enable
rwa	2	4..5	2	RLU write address
R23	1	6	0	RLU(MLU) read address
R01	1	7	1	RLU(ALU) read address
aia	1	8	1	ALU input A mux
alu	2	9:10	1	ALU operation
mib	2	11..12	0	MLU input B mux
mia	2	13..14	0	MLU input A mux
mlu	2	15:16	0	MLU operation
mwa	5	17:21	0	MLU WBUFFER read address
awa	5	22..26	1	ALU WBUFFER read address
va	4	27..30	0	VBUFFER read address
os	2	31..32	2	LLU output address
frm	6	33..38	2	Flag register mask
mfe	1	39	2	MFLAG write enable
mfa	2	40..41	2	MFLAG write address
ife	1	42	2	IFLAG write enable
ifa	2	43..44	2	IFLAG write address
fia	2	45:46	2	FLU input A mux
flu	3	47:49	2	FLU operation
M1c	1	50	2	MAC1 input C mux
M1b	2	51:52	2	MAC1 input B mux
M1a	2	53:54	2	MAC1 input A mux
M0c	2	55:56	2	MAC0 input C mux
M0b	2	57:58	2	MAC0 input B mux
M0a	2	59:60	2	MAC0 input A mux
ce	3	61:63	0,2	Context memory read/write enable
ca	6	64:69	0,2	Context memory address
C3a	4	70:73	2	Context3 memory address
C2a	4	74:77	2	Context2 memory address
C1a	5	78:82	2	Context1 memory address
C0a	2	83..84	2	Context0 memory address

Figure 22



Figure 23


RECEIVING VERTEX DATA IN A BUFFER OF A FIRST SET OF BUFFERS, WHEREIN THE BUFFER IN WHICH THE VERTEX DATA IS RECEIVED IS BASED ON A ROUND ROBIN SEQUENCE
2420
IDENTIFYING AN EMPTY BUFFER OF A SECOND SET OF BUFFERS BASED ON A ROUND ROBIN SEQUENCE, WHEREIN A TRANSFORM MODULE IS COUPLED BETWEEN THE FIRST SET OF BUFFERS AND THE SECOND SET OF BUFFERS
2422
PROCESSING THE VERTEX DATA IN THE TRANSFORM MODULE AFTER THE EMPTY BUFFER OF THE SECOND SET OF BUFFERS IS IDENTIFIED
2424
OUTPUTTING THE VERTEX DATA FROM THE TRANSFORM MODULE TO THE IDENTIFIED EMPTY BUFFER OF THE SECOND SET OF BUFFERS
2426
IDENTIFYING AN EMPTY BUFFER OF A THIRD SET OF BUFFERS BASED ON A ROUND ROBIN SEQUENCE, WHEREIN A LIGHTING MODULE IS COUPLED BETWEEN THE SECOND SET OF BUFFERS AND THE THIRD SET OF BUFFERS
2428
PROCESSING THE VERTEX DATA IN THE LIGHTING MODULE AFTER THE EMPTY BUFFER OF THE THIRD SET OF BUFFERS IS IDENTIFIED
2430
OUTPUTTING THE VERTEX DATA FROM THE LIGHTING MODULE TO THE IDENTIFIED EMPTY BUFFER OF THE THIRD SET OF BUFFERS
2432

Figure 24



Figure 25



Figure 25B



Figure 26



Figure 26A


START
SET-UP
RECEIVE TRIANGLE AND COMPUTE LINE EQUATION COEFFICIENTS
2700
MODIFY LINE EQUATION COEFFICIENTS IF ANY TRIANGLE VERTEX(ES) HAVE A NEGATIVE W-COORDINATE
2702
POSITION A CONVEX POLYGON ON OR NEAR THE TRIANGLE/POLYGON
2704
PROCESS ROW
2706
2710
GOTO JUMP POSITION
JUMP POSITION FOUND ?
YES
NO
2708
END
TRAVERSAL

Figure 27



Figure 27A


START
COMPUTE SENSE POINTS
2800
2706
NO
CAN GO RIGHT ?
2801
2802
YES
STORE RIGHT-HAND NEIGHBOR RECTANGLE AS SNAP-LOCATION
2812
CALCULATE VALUE OF LINE EQNS AT SENSE POINTS OF RECTANGLE
2804
NO
CAN GO DOWN ?
2806
MOVE RECTANGLE LEFT
YES
CALCULATE AND STORE JUMP POSITION
2808
ARE LEFT SENSE POINTS BOTH OUTSIDE EDGE OF THE TRIANGLE ?
NO
2810
YES
2814
NO
IS THERE A SNAP LOCATION?
2826
YES
2816
GOTO SNAP LOCATION
2818
CALCULATE VALUE OF LINE EQNS AT SENSE POINTS OF RECTANGLE
NO
CAN GO DOWN ?
2820
MOVE RECTANGLE RIGHT
YES
CALCULATE AND STORE JUMP POSITION
2822
NO
ARE RIGHT SENSE POINTS BOTH OUTSIDE EDGE OF THE TRIANGLE ?
YES
2824
DONE

Figure 28



Figure 28A



Figure 28B


START
2900
FIRST DIRECTION
WAS PREVIOUS DIRECTION IN A FIRST OR SECOND DIRECTION?
2906
SECOND DIRECTION
CALCULATE VALUE OF LINE EQNS AT 4 SENSE POINTS OF RECTANGLE
2902
ARE SENSE POINTS OF THE FIRST SIDE OF THE RECTANGLE BOTH OUTSIDE EDGE OF THE TRIANGLE ?
NO
MOVE THE RECTANGLE THE FIRST DIRECTION
2904
YES
2905
NO
CAN GO DOWN ?
YES
2908
CALCULATE AND STORE JUMP POSITION
CALCULATE VALUE OF LINE EQNS AT 4 SENSE POINTS OF RECTANGLE
2910
ARE SENSE POINTS OF THE SECOND SIDE OF THE RECTANGLE BOTH OUTSIDE EDGE OF THE TRIANGLE ?
NO
MOVE THE RECTANGLE THE SECOND DIRECTION
2912
YES
2913
NO
CAN GO DOWN ?
2914
YES
CALCULATE AND STORE JUMP POSITION
2916
DONE

Figure 29



Boustrophedonic Footprint Sequence over a Triangle

Figure 29A

Figure 30




START
WAS PREVIOUS MOVEMENT IN A FIRST OR SECOND DIRECTION?
FIRST DIRECTION
SECOND DIRECTION
CALCULATE VALUE OF LINE EQNS AT SENSE POINTS OF RECTANGLE
ARE SENSE POINTS OF THE FIRST SIDE OF THE RECTANGLE BOTH OUTSIDE EDGE OF THE TRIANGLE ?
NO
YES
CAN GO DOWN ?
NO
YES
CALCULATE AND STORE JUMP POSITION
3118
IS RECT PAST LIMIT?
NO
YES
MOVE THE RECTANGLE THE FIRST DIRECTION
STORE STARTING POSITION
3119
CALCULATE VALUE OF LINE EQNS AT SENSE POINTS OF RECTANGLE
ARE SENSE POINTS OF THE SECOND SIDE OF THE RECTANGLE BOTH OUTSIDE EDGE OF THE TRIANGLE ?
NO
YES
CAN GO DOWN ?
NO
YES
CALCULATE AND STORE JUMP POSITION
3120
IS RECT PAST LIMIT?
NO
YES
MOVE THE RECTANGLE THE SECOND DIRECTION
STORE STARTING POSITION
3121
DONE

Figure 31



Swaths: 1-101, then 102-137, then 138-217, then 218-246

Figure 31A



Figure 32



Figure 32A



Figure 32B



Figure 32C